

## **1.5MHz, 0.8A Synchronous Step-Down Converter**


### ❖ GENERAL DESCRIPTION

AX3523 is a high efficiency monolithic synchronous buck regulator using a constant frequency, current mode architecture. The device is available in an adjustable version. Supply current with no load is 250uA and drops to <1uA in shutdown. The 2.5V to 6V input voltage range makes AX3523 ideally suited for single Li-Ion, two to four AA battery-powered applications. 100% duty cycle provides low dropout operation, extending battery life in portable systems. PWM pulse skipping mode operation provides very low output ripple voltage for noise sensitive applications. Switching frequency is internally set at 1.5MHz, allowing the use of small surface mount inductors and capacitors. The internal synchronous switch increases efficiency and decreases need of an external schottky diode. Low output voltages are easily supported with the 0.6V feedback reference voltage. AX3523 is available in small TSOT-23-5L and TDFN-6L packages.

### ❖ FEATURES


- 2.5V to 6 V Input Voltage Range
- Output Voltage from 0.6V to VIN
- High Efficiency: Up to 95%
- 1.5MHz Constant Frequency Operation
- Up to 0.8A Output Current
- Quiescent Current: 250uA (Typical)
- No Schottky Diode Required
- Current Mode Operation for Excellent Line and Load Transient Response
- Current limit, Enable function
- Short Circuit Protect (SCP)
- Build in soft start function
- $\leq 1\mu\text{A}$  Shutdown Current
- TSOT-23-5L and TDFN-6L Pb-Free packages

## ❖ BLOCK DIAGRAM



## ❖ PIN ASSIGNMENT

The packages of AX3523 are TSOT-23-5L and TDFN-6L; the pin assignment is given by:



Name	Description
EN	Enable pin H : normal operation L : Shutdown
VIN	Power Supply Input Pin
SW	Switch output pin. Connect external inductor here. Minimize trace area at this pin to reduce EMI.
GND	Ground Pin
FB	Output Feedback pin
NC	No Connect.

❖ ORDER/MARKING INFORMATION

Order Information	
<p align="center"><b>AX3523XXX</b></p> <div style="display: flex; justify-content: space-around;"> <div> <p>Package Type</p> <p>BT: TSOT-23-5L</p> <p>Z6: TDFN-6L (2*2)</p> </div> <div> <p>Packing</p> <p>A : Taping</p> </div> </div>	
Top Marking (TSOT-23-5L)	Top Marking (TDFN-6L)
<p><b>GKYWX</b> → ID Code: internal</p> <p>↓</p> <p>AX3523</p> <p>WW: 01~26(A~Z) 27~52(a~z)</p> <p>Year: A = 2010 1 = 2011</p>	<p><b>GL</b> → AX3523</p> <p><b>YWX</b> → ID code: internal</p> <p>WW: 01~26(A~Z) 27~52(a~z)</p> <p>Year: A=2010 1=2011</p>

❖ ABSOLUTE MAXIMUM RATINGS (at T<sub>A</sub>=25°C)

Characteristics	Symbol	Rating	Unit
VIN Pin Voltage	V <sub>IN</sub>	V <sub>SS</sub> - 0.3 to V <sub>SS</sub> + 7	V
Feedback Pin Voltage	V <sub>FB</sub>	V <sub>SS</sub> - 0.3 to V <sub>CC</sub> + 0.3	V
EN Pin Voltage	V <sub>EN</sub>	V <sub>SS</sub> - 0.3 to V <sub>CC</sub> + 0.3	V
Switch Pin Voltage	V <sub>SW</sub>	V <sub>SS</sub> - 0.3 to V <sub>CC</sub> + 0.3	V
Peak SW Sink and Source Current	I <sub>PSW</sub>	1.4	A
Power Dissipation	PD	(T <sub>J</sub> -T <sub>A</sub> ) / θ <sub>JA</sub>	mW
Storage Temperature Range	T <sub>ST</sub>	-40 to +150	°C
Operating Temperature Range	T <sub>OP</sub>	-40 to +85	°C
Junction Temperature	T <sub>J</sub>	+125	°C
Thermal Resistance from Junction to case	TDFN-6L	25	°C/W
	TSOT-23	110	
Thermal Resistance from Junction to ambient	TDFN-6L	120	°C/W
	TSOT-23	250	

Note: θ<sub>JA</sub> is measured with the PCB copper area of approximately 1 in<sup>2</sup>(Multi-layer). That need connect to GND pin of the AX3523.


## ❖ ELECTRICAL CHARACTERISTICS

( $V_{IN} = V_{EN} = 3.6V$ ,  $T_A = 25^\circ C$ , unless otherwise specified) (Note)

Characteristics	Symbol	Conditions	Min	Typ	Max	Units
Input Voltage Range	$V_{IN}$		2.5	-	6	V
Feedback Voltage	$V_{FB}$	$T_A = +25^\circ C$	0.5880	0.6000	0.6120	V
		$T_A = 0^\circ C \leq T_A \leq 85^\circ C$	0.5865	0.6000	0.6135	
		$T_A = -40^\circ C \leq T_A \leq 85^\circ C$	0.5820	0.6000	0.6180	
Feedback Bias Current	$I_{FB}$	$V_{FB} = 0.65V$	-	-	$\pm 30$	nA
Quiescent Current	$I_{CCQ}$	$V_{FB} = 1V$		250	350	$\mu A$
Shutdown Supply Current	$I_{SD}$	$V_{EN} = 0V$	-	0.1	1	$\mu A$
Switching Current Limit	$I_{LIMIT}$		1.0	1.2	-	A
Line Regulation	$\Delta V_{OUT}/V_{OUT}$	$V_{IN} = 2.5V \sim 6V$	-	0.04	0.4	%/V
Load Regulation	$\Delta V_{OUT}/V_{OUT}$	$I_{OUT} = 0.01$ to $0.8A$	-	0.5	-	%
Oscillation Frequency	$F_{OSC}$	SW pin	1.2	1.5	2.0	MHz
$R_{DS(ON)}$ of P-CH MOSFET	$R_{DS(ON)}$	$I_{SW} = 300mA$	-	0.40	-	$\Omega$
$R_{DS(ON)}$ of N-CH MOSFET	$R_{DS(ON)}$	$I_{SW} = -300mA$	-	0.35	-	$\Omega$
EN pin logic input threshold voltage	$V_{ENL}$		-	-	0.6	V
	$V_{ENH}$		1.2	-	-	
EN Pin Input Current	$I_{EN}$		-	$\pm 0.1$	$\pm 1$	$\mu A$
Efficiency	EFFI	$V_{IN} = 5V$ , $V_{OUT} = 3.3V$ , $I_{OUT} = 0.5A$	-	92	-	%
Thermal shutdown	$T_{DS}$		-	140	-	$^\circ C$
Thermal shutdown Hysteresis	$T_{SH}$		-	30	-	$^\circ C$

Note: 100% production test at  $+25^\circ C$ . Specifications over the temperature range are guaranteed by design and characterization.

## ❖ APPLICATION CIRCUIT



## ❖ FUNCTION DESCRIPTIONS

### Operation

AX3523 is a monolithic switching mode step-down DC-DC converter. It utilizes internal MOSFETs to achieve high efficiency and can generate very low output voltage by using internal reference at 0.6V. It operates at a fixed switching frequency, and uses the slope compensated current mode architecture. This step-down DC-DC Converter supplies minimum 0.8A output current at input voltage range from 2.5V to 6V.

### Current Mode PWM Control

Slope compensated current mode PWM control provides stable switching and cycle-by-cycle current limit for excellent load and line transient responses and protection of the internal main switch (P-Ch MOSFET) and synchronous rectifier (N-CH MOSFET). During normal operation, the internal P-Ch MOSFET is turned on for a certain time to ramp the inductor current at each rising edge of the internal oscillator, and switched off when the peak inductor current is above the error voltage. The current comparator,  $I_{COMP}$ , limits the peak inductor current. When the main switch is off, the synchronous rectifier will be turned on immediately and stay on until either the inductor current starts to reverse, as indicated by the current reversal comparator,  $I_{ZERO}$ , or the beginning of the next clock cycle.

## ❖ APPLICATION INFORMATION

### Setting the Output Voltage

Application circuit item shows the basic application circuit with AX3523 adjustable output version. The external resistor sets the output voltage according to the following equation:

$$V_{OUT} = 0.6V \times \left(1 + \frac{R1}{R2}\right)$$

Table 1 Resistor select for output voltage setting

V <sub>OUT</sub>	R1	R2
1.2V	100K	100K
1.5V	150K	100K
1.8V	300K	150K
2.5V	470K	150K
3.3V	120K	540K

## Inductor Selection

For most designs, the AX3523 operates with inductors of 1μH to 4.7μH. Low inductance values are physically smaller but require faster switching, which results in some efficiency loss. The inductor value can be derived from the following equation:

$$L = \frac{V_{OUT} \times (V_{IN} - V_{OUT})}{V_{IN} \times \Delta I_L \times f_{OSC}}$$

Where is inductor Ripple Current. Large value inductors lower ripple current and small value inductors result in high ripple currents. Choose inductor ripple current approximately 30% of the maximum load current 800mA, ΔI<sub>L</sub>=240mA.

Table 2 Inductor select for output voltage setting (V<sub>IN</sub>=5V)

V <sub>OUT</sub>	1.2V	1.5V	1.8V	2.5V
Inductor	2.7uH	2.7uH	2.7uH	2.2uH
Part Number WE-TPC	7440430027	7440430027	7440430027	7440430022

Note: Part type MH or M ([www.we-online.com](http://www.we-online.com))

For output voltages above 2.0V, when light-load efficiency is important, the minimum recommended inductor is 2.7μH. For optimum voltage-positioning load transients, choose an inductor with DC series resistance in the 50mΩ to 150mΩ range. For higher efficiency at heavy loads (above 200mA), or minimal load regulation (but some transient overshoot), the resistance should be kept below 100mΩ. The DC current rating of the inductor should be at least equal to the maximum load current plus half the ripple current to prevent core saturation (800mA+120mA).

## Input Capacitor Selection


The input capacitor reduces the surge current drawn from the input and switching noise from the device. The input capacitor impedance at the switching frequency shall be less than input source impedance to prevent high frequency switching current passing to the input. A low ESR input capacitor sized for maximum RMS current must be used. Ceramic capacitors with X5R or X7R dielectrics are highly recommended because of their low ESR and small temperature coefficients. A 4.7μF ceramic capacitor for most applications is sufficient.

## Output Capacitor Selection

The output capacitor is required to be 10uF to keep the output voltage ripple small and to ensure regulation loop stability. The output capacitor must have low impedance at the switching frequency. Ceramic capacitors with X5R or X7R dielectrics are recommended due to their low ESR and high ripple current.

❖ PACKAGE OUTLINES

(1) TSOT-23-5L




Symbol	Dimensions in Millimeters			Dimensions in Inches		
	Min.	Nom.	Max.	Min.	Nom.	Max.
A	-	-	1.10	-	-	0.043
A1	0.00	-	0.10	0	-	0.004
A2	0.70	0.90	1.00	0.028	0.035	0.039
b	0.30	0.40	0.50	0.012	0.016	0.020
C	0.08	0.14	0.20	0.003	0.006	0.008
D	2.80	2.90	3.00	0.110	0.114	0.118
E	2.60	2.80	3.00	0.102	0.110	0.118
E1	1.50	1.60	1.70	0.059	0.063	0.067
e	0.95 BSC.			0.037 BSC.		
e1	1.90 BSC.			0.075 BSC.		
L	0.30	0.45	0.60	0.012	0.018	0.024
L1	0.60 REF.			0.024 REF.		
L2	0.25 BSC.			0.010 BSC.		
y	-	-	0.10	-	-	0.004
R	0.10	-	-	0.004	-	-
θ	0°	-	8°	0°	-	8°


JECED outline: MO-193 AB




(2) TDFN-6L (2\*2 0.75mm)



(Top View)



(Bottom View)



(SIDE View)

Symbol	Dimensions in Millimeters			Dimensions in Inches		
	Min.	Nom.	Max.	Min.	Nom.	Max.
A	0.70	0.75	0.80	0.028	0.030	0.031
A1	0.00	0.02	0.05	0.000	0.001	0.002
A3	0.203 REF.			0.008 REF.		
b	0.20	0.28	0.35	0.009	0.011	0.013
D	1.95	2.00	2.05	0.077	0.079	0.081
D2	1.35	1.50	1.65	0.055	0.059	0.063
E	1.95	2.00	2.05	0.077	0.079	0.081
E2	0.75	0.90	1.05	0.031	0.035	0.039
e	0.65 BSC.			0.026 BSC.		
L	0.20	0.30	0.40	0.008	0.012	0.016